

MICHIGAN  
DEPARTMENT OF TRANSPORTATION  
SPECIAL PROVISION  
FOR  
**GROUNDING, BONDING, LIGHTNING PROTECTION AND SURGE PROTECTION  
FOR ELECTRICAL SYSTEM EQUIPMENT**

ITS:JDF

1 of 6

APPR:JVG:MS:04-14-26

FHWA:APPR:04-16-26

**a. Description.** This work consists of installing functional and unobtrusive grounding and bonding system, lightning protection for all poles and structures, and surge protection for all conductors entering or leaving equipment cabinets and in equipment in housings at the specified locations shown on the plans.

1. Comply with the *National Fire Protection Association (NFPA) 70 - NEC*, latest edition adopted by the State of Michigan.
2. Adhere to *NFPA 780 - Lightning Protection Code* as specified herein.
3. Adhere to *UL* listings as specified throughout this special provision.
4. Comply with the *NESC*.

Identify to the Engineer any conflicts between the requirements of regulatory agencies and the contract for this project.

Submit product data for each type of product used (i.e. "shop drawings") for approval by the Engineer before work commences.

As directed by the Engineer, submit a system plan, locating air terminals, conductor routing, supports, connectors, ground rods, and connection, mounting, and splicing details. Identify where special means are incorporated to avoid galvanic reactions due to dissimilar metals.

**b. Materials.** For each component required in the contract, meet the following requirements:

1. Grounding and Bonding.
  - A. Grounding Electrodes (driven rods). Furnish ground rods that are 3/4-inch diameter by 10 feet long, made of copper-clad steel with a minimum of 10 mils copper cladding, complying with *ANSI/UL 96/96A* and *ANSI/NEMA GR-1*.
  - B. Ground Bus Bar Kit. Furnish a ground bar kit with screw down terminals sized per grounding and grounding electrode conductors that must be connected. Furnish a ground bar kit with a mounting kit appropriate for intended installation (for example, on an equipment rack in a damp location).
  - C. Grounding Conductors. Unless noted otherwise, ensure below grade conductors used for bonding grounded systems are stranded #6 AWG copper conductors, and

ensure bonding conductors routed inside enclosures and cabinets are green insulated #6 AWG conductors.

D. Bonding Kits. Ensure all bonding kits are *UL* listed and furnish adequate surface area for intended application; ensure bonding kits being used as part of a lighting protection system are sized in accordance with *NFPA 780*. Ensure enclosure ground lugs are furnished and installed by the enclosure manufacturer.

2. Lightning Protection. Ensure all lightning protection materials are *UL 96 listed for lightning protection, Class II*.

Do not use a combination of materials that may cause electrolytic coupling of such a nature that corrosion is accelerated. This includes copper in direct contact with aluminum and copper in direct contact with galvanized steel in exterior or other wet locations. Ensure two dissimilar metals are not connected unless preventative measures inhibit galvanic corrosion.

3. Surge Protection.

A. Furnish protectors that are *UL 497B* listed to protect the twisted pair cable that meet or exceed the following minimum requirements:

(1) Maximum clamping voltage.

(a) Common-mode. twice peak signal voltage.

(b) Differential-mode. 50 volts (V) to ground.

(2) Technology. Two-stage using gas discharge tube and metal-oxide varistor or approved equal.

(3) Overcurrent protection. Integral polymeric positive temperature coefficient (PPTC) device.

(4) Maintainability. Replaceable without tools.

(5) Protect microwave vehicle detection system (MVDS) and DC power cables with grounded metal oxide varistors of appropriate voltages. Furnish devices with surge capacity of at least 3,000 Amperes (A). Ensure surge protection for these devices are in accordance with device manufacturer specific guidelines.

(6) Protect power over Ethernet (POE) devices, with protectors designed for POE applications.

B. Furnish protectors that are *IEEE 802.3at* and *International Electrotechnical Commission (IEC) 61643-21* compliant.

C. Incoming Power Service.

(1) ITS Cabinets. Protect 120/240V incoming power service to equipment cabinet with *UL 1449* listed Type 2 devices. They must meet the following requirements:

- (a) Terminals. #12 AWG;
- (b) Surge Capacity Rating. Minimum 40 kilo ampere (kA)/mode, 80kA/phase;
- (c) Voltage Protection Rating. L-N, L-G, N-G, L-L;
- (d) Short Circuit Current Rating. 100kA;
- (e) Nominal discharge current of 20,000A;
- (f) Line protection. L-N, L-G, L-L, and N-G;
- (g) Indicators. LED status indication; and
- (h) Compatibility. Compatible with the main circuit breaker.

(2) Signal Cabinets. Surge protection for incoming power service for signal cabinets is specified and paid for under 20SP-820Z - National Electrical Manufacturers Association Type Traffic Signal Cabinet.

**c. Construction.** Install equipment, materials, and devices in accordance with equipment manufacturer's written instructions and in compliance with applicable installation standards. Any conduit material will be included in the contract unit price for the installation of conduit.

Furnish exothermically welded connections below grade and in areas exposed to visible moisture. In locations where damage to existing cable is possible permanent mechanical clamp (listed for wet locations) may be used.

Ensure terminals and connectors are *UL* listed and sized for the conductors that will be used. Use clips, harnesses, or ties in cabinets to keep grounding electrode conductors and bonding conductors out of the way of service activities.

Permanently affix distinct wire numbers or alphanumeric labels to each cable.

1. Grounding and Bonding. Furnish and install insulated and/or bare wire and cables, as shown on the plans. Ensure

A. Installation.

(1) Bond metallic items, such as poles, towers, horizontal and vertical structures, metal conduit junction boxes, fences, and pad mounted equipment to form a low-impedance ground plane.

(2) Furnish equipment grounding conductors and grounding electrode conductors that conform to the *NEC*. Use of metallic conduit to replace grounding conductors is prohibited. Connection of grounding conductor to neutral bus bar (grounded) conductor must only occur at service disconnect.

(3) Bond all metallic conduits, boxes, and cabinets to the grounding system. Furnish metallic conduit terminations with grounding bushings. Where not otherwise noted ensure all bonding conductors are green insulated #6 AWG.

(4) Bond electrical grounding conductors to lightning protection system grounding conductors. Ensure all bonding conductors in conduits, cabinets, structures, or other appurtenances are green insulated #6 AWG. Ensure all bonding conductors with direct earth contact are bare #6 AWG.

(5) Install grounding electrodes as needed to complete the grounding system.

B. Testing.

(1) Measure ground grid resistance using 3-point method per *IEEE 81* with earth ground test meter or clamp-on method in accordance with device manufacture direction. Install additional ground rods and conductors as required and re-measure until resistance to ground is equal to or less than 10 Ohms. Additional ground rods, conductors, conduit, and ancillary materials required to achieve stated resistance are included in pay items below and will not be paid for separately. Test the ground rods and conductors in the presence of the Engineer. Furnish documentation to the Engineer of ground grid measurement results for each site location tied to a single grounding system.

(2) Furnish all test equipment required to test the copper cabling in accordance with the parameters specified.

2. Lightning Protection. Install lightning protection system in accordance with the following requirements:

A. Install down conductors, per *NFPA 780*, in a direct path from air terminals to ground connections free of splices and sharp bends; except when the pole is used as the down conductor or where noted on the plans. No bend of a conductor is to form a final angle of more than 90 degrees nor have a bend radius of less than 8 inches.

B. Conceal and protect down conductors and interior wiring from view at all exterior locations above grade as practical. Conceal cable down conductors within structural elements. Ensure cable down conductors are enclosed within conduit for all installations. Reference the plan details for conduit size. Use conduit or guards to protect the conductor to a point 10 feet above grade or as shown on the plans where down conductors are exposed to environmental hazards at grade level.

C. Secure exposed cable conductors to the structure at intervals not exceeding 3 feet. Use fasteners, nails, screws, straps, or bolts for the intended application and of the same material as the conductor or of electrolytically compatible materials. Galvanized or plated steels are prohibited.

D. Use a grounding electrode for the lightning protection system, located in the dedicated composite lightning protection handhole(s). Install additional ground rods and conductors as required and re-measure until resistance to ground is equal to or less than 10 Ohms.

E. Bond the lightning protection system to common grounding system as shown on the plans.

F. Install air terminals on all structures as shown on plans.

3. Surge Protection.

A. Install the required number and type of modular surge protector devices, as determined by the number and type of incoming lines.

B. Arrange the equipment and cabinet wiring to minimize leader length to surge protector.

C. Avoid sharp bends in leaders to surge protectors.

4. Warranty. Furnish all surge protective devices covered by this special provision with a standard manufacturer’s warranty, transferable to MDOT. All the surge protective devices must carry a warranty (parts and labor) of 3 years from the date of shipment with at least 2 years of warranty remaining at the start of burn-in. Furnish warranty and other applicable documents from the manufacturer, and a copy of the invoice showing the date of shipment, to the Engineer prior to final written acceptance.

**d. Measurement and Payment.** The completed work, as described, will be measured and paid for at the contract unit price using the following pay items:

<b>Pay Item</b>	<b>Pay Unit</b>
Grounding, Bonding, and Surge Protection .....	Lump Sum
Lightning Protection, Pole.....	Each
Lightning Protection, Structure, ESS Tower.....	Each
Lightning Protection, Structure, Large Dynamic Message Sign .....	Each
Lightning Protection, Structure, Small Dynamic Message Sign.....	Each
Lightning Protection, Structure, Type E Truss.....	Each
Lightning Protection, Structure, Type E Cantilever .....	Each

1. **Grounding, Bonding, and Surge Protection** will be measured and paid for as a lump sum for all work to ground each ITS component as described by this special provision and as shown on the plans. Partial payments will be made based as shown below:

Approved Equipment Submittals	50%
Completed Installation	75%
Inspection by Jurisdictional Authorities	100%

2. **Lightning Protection, Pole** will be measured and paid for as each lightning protection system furnished for protection of equipment on a pole, mast arm or truss arm with Class II materials.

3. **Lightning Protection, Structure, ESS Tower** will be measured and paid for as each lightning protection system furnished for protection of an Environmental Sensor Station lattice tower, using the structure as a down conductor.

4. **Lightning Protection, Structure, Large Dynamic Message Sign** and **Lightning Protection, Structure, Small Dynamic Message Sign** will be measured and paid for as each lightning protection system furnished for protection of a Dynamic Message Sign, using the structure as a down conductor.

5. **Lightning Protection, Structure, Type E Truss** and **Lighting Protection, Structure, Type E Cantilever** will be measured and paid for as each lightning protection system furnished for protection of a Lane Control System on a Type E Truss or Type E Cantilever, using the structure as a down conductor.